

Receiver Box S

Ultra compact integrated stereo amp including FM tuner

- Smallest High-End receiver on the market
- 2x 30W @ 4 ohms / 2x 25W @ 8 ohms
- 2 stereo line inputs
- **NEW!** Improved FM tuner with higher sensitivity
- 99 presets and auto store and search function
- High-resolution dot-matrix display (blue)
- Indication of signal strength, precise center of station, stereo/mono reception
- Easy control via IR remote or 3 buttons on faceplate
- Metal casing protects against vibration and interference
- Faceplate silver or black

Technical data

Power output	2x 25W / 30W at 8 / 4 ohms (both channels driven)
Tuning range FM-band	87,5 - 108MHz (50kHz steps)
Programmable presets	99
THD tuner	0,05% / Δf 75kHz and f mod 1kHz
Stereo separation	30dB / Δf 75kHz and f mod 1kHz
Sensitivity	7dB/ μ V mono, 17dB/ μ V stereo /75 ohms
Frequency response	20Hz - 20kHz ($\pm 0,2$ dB)
Channel separation	> 40dB at 20kHz
Noise floor	> -100dB (A weighted)
THD amplifier	< 0,005% at 10W
Gain	22dB
Line-level inputs	1 pair RCA/phono sockets 3-pole 3,5mm co-axial jack
Input impedance	20kohms
Antenna input	1x co-axial DIN-socket (75 ohms)
Outboard power supply	20V/3A DC (peak 7A DC)
Power consumption standby	< 1 Watt
Dimension W x H x D (D with sockets)	103 x 36 x 104 (122)mm
Weight	670g without power supply



Receiver Box S - Ultra compact stereo integrated amp with FM tuner!

Receiver Box S is an audiophile piece of micro electronics and real hifi miracle! Receiver Box S includes top-class components: line preamplifier, FM tuner with 99 presets & audiophile power amplifier, which are able to substitute 3 separate audio components. With the IR remote (included) volume level, input selection and FM-Tuner easily can be controlled. Receiver Box S is for sure the smallest audiophile Stereo receiver on the market, that proves micro-sized components need not to compromise in sound quality!



Back view >

- ◇ Inputs
- ◇ Antenna
- ◇ Speaker connection
- ◇ Power

< black version

